

RFA Tank Mounted Mini-Type Return Filters



How to order

RFA	-25	x 20	F	-Y
Series	Nominal flow (L/min)	Filtration mesh (μm)	Connection L: Thread F: Flange	Indicator Y: With CYB-I indicator < DC24V C: With CY-II indicator < 220V Without indicator

Specification

Model	Nominal flow L/min	Filtration mesh μm	Size	Press. MPa	Press. loss		Indicator		weight (kg)	Model of element
					Open	Max.	V	A		
RFA-25 x *L- $\frac{C}{Y}$	25	1	15	1.6	< 0.075	0.35	12	2.5	0.85	FAX-25x*
RFA-40 x *L- $\frac{C}{Y}$	40		20						0.9	FAX-40x*
RFA-63 x *L- $\frac{C}{Y}$	63		25						1.5	FAX-63x*
RFA-100 x *L- $\frac{C}{Y}$	100		32						1.7	FAX-100x*
RFA-160 x *L- $\frac{C}{Y}$	160		40						2.7	FAX-160x*
RFA-250 x *L- $\frac{C}{Y}$	250		10						4.35	FAX-250x*
RFA-400 x *L- $\frac{C}{Y}$	400		20						6.15	FAX-400x*
RFA-630 x *L- $\frac{C}{Y}$	630		30						8.2	FAX-630x*
RFA-800 x *L- $\frac{C}{Y}$	800		90						8.9	FAX-800x*
RFA-1000 x *L- $\frac{C}{Y}$	1000		90						9.96	FAX-1000x*

Symbol

